

>



Model Number: 165603

NorthStar 165603 Generator 8000 Surge Watts 6600 Rated Watts EPA Phase 3/CARB Compliant Recoil Start 390cc

Manufacturer: NorthStar

NorthStar 165603 Generator 8000 Surge Watts 6600 Rated Watts EPA Phase 3/CARB Compliant Recoil Start

Overview

This new NorthStar 8000 Watt Generator packs more power, greater fuel efficiency and quieter operation into a new, space-saving design.

Features + Benefits

- Digital CDI ignition offers excellent starting and high-power output
- Full roll cage with antirip mounts and rollover valve prevent damage and fuel leaks if tipped
- Solid base prevents grass, dirt and dust from getting into the engine and alternator
- V-mount vibration isolation system extends generator life
- High-quality 100% copper-wound brushless head with low THD for safe use with sensitive equipment
- Includes voltmeter
- EPA Phase 3 and CARB compliant
- Optional wheel kit, Item# 165620, adds convenient portability

What's Included

- (1) Generator

Key Specs

Surge Watts

8,000

Rated Watts

6,600

Start Type

Recoil

>

Engine

Honda GX390 OHV

Run Time

10 hours @ 1/2 load

Receptacles (qty.)

Four duplex 120V, 20A outlets; one 120/240V, 30A locking outlet; one 120V, 30A locking outlet; 12VDC outlet

Noise Level (dB)

74.5

Fuel Type

Gasoline

Fuel Capacity (gal.)

6.5

Low Oil Shutdown

Yes

Dimensions L x W x H (in.)

25 3/4 x 21 1/4 x 22 1/4

>

Ship Weight

200.0 lbs

Item#

165603

Manual

Optional

Generator Grounding Kit Bonding Parts 18012017 Self Install

BE Pressure 85.508.003 Champion Power 48036 L14-30P X Four 5-20R
Generator Power Cord Adapter

Need Help Loading & Unloading? Check Out Our Selection of Loading Ramps
[Click Here](#)

Availability: This product was added to our catalog on Monday 21 March, 2011